



SENSOR SWITCH

Item.#	RBS06 Series	Description	TILT SWITCH	Version	V97.0
Page	1 of 4		Date	Sep. 30, 2008	

● APPLICATIONS

1. Horizontal Tilt Detecting
2. Tilt Detecting: Angle can be set up by PCB Layout
3. Up-side down Detecting



● FEATURES

1. Small size & compact space.
2. Balls are gold plated to enhance the life.
3. All plastic material subject to industrial purpose meets with UL94V-0 grade; high temperature and fireproof function.
4. Suitable to IC trigger signal.
5. Complete replacement of mercury switch and meet with environmental protection.

● PATENTS

1. TAIWAN Patent NO. 172094

● DIMENSIONS / OPERATION / P.C.B. LAYOUT (Unit: mm, Tolerance: ±0.25mm)

<p>RBS 06 01 00</p>	<p>Tilt Angle Range <math>\theta &gt; 10^\circ; \theta &lt; -10^\circ</math></p>	<p>P.C.B. Layout (DIP) / Top View</p>
<p>RBS 06 02 00</p>	<p>Tilt Angle Range <math>\theta &gt; 10^\circ; \theta &lt; -10^\circ</math></p>	<p>P.C.B. Layout (DIP) / Top View</p>



## SENSOR SWITCH

Item.#	RBS06 Series	Description	TILT SWITCH	Version	V97.0
Page	2 of 4		Date	Sep. 30, 2008	

## ● ELECTRICAL CHARACTERISTICS

1.	Contact Rating	25mA , 24VDC
2.	Contact Resistance	100Ω max.
3.	Differential Angle	Refer to the drawing
4.	Insulation Resistance	1000MΩ min. At 100 VDC
5.	Dielectric Strength	500 VDC min. for 1 minute
6.	Capacitance	5pF max

## ● MECHANICAL CHARACTERISTICS

1.	Temperature Range	Operating: -25°C to +85°C Storage: -40°C to +85°C
2.	Pull Force of Terminal	500 gf for 1 minute
3.	Operation Life	100,000 Cycles
4.	Conductive Rate (Switch-on Rate)	min. over 90%
5.	Humidity	95% RH, 40° C for 96 hrs.
6.	Solder ability	After flux 245±5°C for 5±0.5 seconds 95% coverage

## ● BILL OF MATERIAL

1.	Housing	ZINC Alloy, Tin Plated over Nickel
2..	Cover	Class-Fiber Polyamide, UL 94-0
3.	Terminal	Copper Alloy, Gold Plated over Nickel
4.	Ball	Copper Alloy, Gold Plated over Nickel
5.	Steel Ball	Stainless Steel



## SENSOR SWITCH

Item.#	RBS06 Series	Description	TILT SWITCH	Version	V97.0
Page	3 of 4		Date	Sep. 30, 2008	

● PACKAGE (Minimum Order Quantity: One Bag)

	Part Number	Package	Quantity	Total	Size
1.	RBS060100	PE Bag	500 pcs	500 pcs	12.7 x 17.8 (cm)
		Inner Box	10 Bags	5,000 pcs	36 x 20 x 9 (cm)
	RBS060200	Carton	3 Boxes	15,000 pcs	36 x 28 x 23 (cm)

● NOTE

1. Suggestion for Application : Application in occasions that require vibration functions, adding design of "ON DELAY" is recommended. For great vibration, Optical type products are recommended.
2. Suggestion Contact Rating: 5 mA.
3. Conductive Rate: To test the conductivity (Switch-on Rate) of one switch individually for 100 times, if the switch conductive 95 times, we call the "conductive rate" is 95%.
4. For the continued product improvement as one of the company policy, specifications may change or update without notice. The latest information can be obtained through our sales offices. Normally, all products are supplied under our standard conditions.

● PRECAUTIONS FOR USE

1. The product is used mainly in electronic devices such as automotive devices, visual devices, home electrical appliances, information devices and communication settings. If the products is intended to be used for other endurance equipments requiring higher safety and reliability such as life support system, space and aviations devices, disaster and safety system, it's necessary to make verification of conformity or contact us for the details before using.
2. Don't try to clean the switch with a solvent or similar substance after the soldering process.
3. The switch might be damaged if using the water-soluble flux.
4. Don't use the switch in the environment with high humidity or other bedewing

4F-3, No. 171, Sec. 2, Chang An E. Rd., Taipei, Taiwan, R. O. C.

TEL: 886-2-27111093~5

FAX: 886-2-27310902

E-mail: jinzon@ms2.hinet.net

Http:// www.jinzon.com.tw/

JIN ZON ENTERPRISE CO., LTD.

駿融企業有限公司



## SENSOR SWITCH

Item.#	RBS06 Series	Description	TILT SWITCH	Version	V97.0
Page	4 of 4		Date	Sep. 30, 2008	

possibility, as it may cause leaking among the terminals.

5. It might catch fire if the rating exceeds the specifications. Never use the switch beyond the rating.