

BURAKOOL

Switches & Sensors



Tel: (574)-264-6099 Ext 501

Tel: (888) 847-6552: Fax: (574) 293-8013

Mission Statement

American Electronic Components, Inc., is a designer and manufacturer of electrical and electronic components focused on niche markets for sensors, switches, and relays. The Company is dedicated to providing the highest quality components and service which exceed the needs and wants of its customers. We are growth oriented and practice integrity and fairness when dealing with all stakeholders of the business. We will continue our leadership position and display a marketing orientation while satisfying customers with products that complement our existing sensor, switch, and relay technology. AEC is committed to earning a profit, so the Company will remain financially strong and perpetuate this philosophy.

Lab Accreditation



The AEC Quality Assurance Laboratory is accredited by the American Association for Laboratory Accreditation (A2LA). A2LA is important to AEC and its customers since it allows us to perform timely design validation, product validation, and continuous conformance evaluation on our products. This accreditation is a critical asset and demonstrates AEC's continuing commitment to the pursuit of quality.

Features

Hermetically Sealed Contacts are impervious to external contaminants

Self-renewing contacts No contacts to clean or adjust

Reliable Liquid mercury contacts

Long Life Superior performance over conventional contacts

Low Contact Resistance Stable over life

Metal Construction Unlike glass, virtually indestructible





Glass Breaks — Metal Bounces



Tel: (574)-264-6099 Ext 501

Tel: (888) 847-6552: Fax: (574) 293-8013

Options

Durakool switches and sensors are available in normally-open or normally-closed contact forms, and in sizes for milli-amp signal loads to 25-amp power switching loads. They are available in single-throw and double-throw designs and can be insulated or non-insulated.

This catalog contains standard parts, but custom designs are available.

Applications



A sensor automatically shuts off a laptop computer when the screen is closed.



A motion sensor automatically shuts off an iron after a period of inertia.

Today's growing use of microprocessors with printed circuit boards in appliance, automotive, communication and other fields is creating many new applications uniquely suited to Durakool switches and sensors. Worldwide efforts focusing on product safety are opening many new motion, position, and tip-over applications, such as shut-offs for area space heaters.

Durakool switches have proven themselves in a wide variety of applications. Some of these include:

- ▲ Microprocessor control
- Convenience lights in automobile trunks, glove boxes, etc.
- Convenience lamps in freezer lids
- Pump floats
- ▲ Motor or lamp control in dirty environments
- Indication of position or inclination
- Triggers for alarm/security systems
- ▲ Machine limit switches
- Remote control of relays/solenoids
- ▲ Electronic games and toys
- ▲ G-Force/Inertia



Tel: (574)-264-6099 Ext 501 Tel: (888) 847-6552: Fax: (574) 293-8013

URAKOOL Non-Insulated Tilt and Position Switches

Durakool tilt switches "make" when the electrode is tilted below horizontal and "break" when tilted above horizontal. Total travel from "make" to "break" is the "Maximum Included Angle" shown below. The component to which the switch is

attached must have a total tilt angle greater than the "Maximum Included Angle" for proper operation. "G" series switches are mercury-to-mercury; "A" series are mercury-to-metal.

	Angle snown below. The component to which the switch is mercury-to-metal.							
TYPE/SERIES	A½S	A½N	A1/2	AIS	AIN	G5N	G8N	GION
PART NUMBER	4929	5002	4859**	AIS-017	20144	3822	3825	3765
Must Make/Break Angle* Max. Included Angle	-7°/+7° —	 15°	-2°/+15° —	 16°	-1°/+1° 1.5°	<u></u>	<u></u>	9°
Note: Switches are pictured in normally closed position.	4		4					
*Make/break angles are electrode +(above)/ -(below) 0° horizontal reference.	is a second		11		-	4	4	¥
ELECTRICAL RATINGS								
AC Amps, 60Hz 120V 240V 480V	111	1.0 0.4 —	Ξ	:	1.0 0.7 —	7.0 5.0 —	15.0 11.0 8.0	25.0 19.0 13.0
DC Amps 120V 240V	#	0.5 0.4	=	:	0.5 0.4	5.0 4.0	8.0 6.0	13.0 10.0
Tungsten Lamp (120V, 60Hz), Watts	_	60	_	75	100	700	1000	1700
Motor Load, Horsepower AC 60Hz, 120-480V DC, 120-240V	=	=	=	=	1	0.33 0.25	0.50 0.33	1.0 0.5
Contact Resistance Milliohms (Typical)	=	80	150	30	200	3	3	3
Standoff Voltage, Contact to contact	_	1250	-	1500	1500	1500	2500	3000
ENGLISH DIMENSIONS Lbs./100 pcs. Body Length, in. (less leads) Max. Diameter, in.	0.25 0.27	0.33 0.39 0.27	0.39 0.27	0.68 0.52 0.34	1.10 1.00 0.389	1.88 1.36 0.42	4.59 1.68 0.50	5.62 1.90 0.62
METRIC DIMENSIONS Kg/100 pcs. Length, cm Max. Diameter, cm	0.99 0.67	0.15 1.91 0.67	1.94 0.67	0.31 1.52 0.85	0.50 2.50 0.90	0.85 3.97 1.06	2.08 4.74 1.27	2.55 5.36 1.56
Finish	Tin	Tin	Nickel**	Cadmium	Rust Inhibited	Rust Inhibited	Rust Inhibited	Rust Inhibited

Must Break Included Angle Must Make

^{# 0.5} Amps @ 12 VDC Max.
* I Amp, 6-24V, AC/DC
**Also Available Tin Plated (Part Number 4954)



Tel: (574) 264-6099 Ext 501 Tel: (888) 847-6552; Fax: (574) 293-8013

DURAKOOL Insulated Tilt and Position Switches

TYPE/SERIES	A 1/2	AI	G5Z	G8Z	GI0Z
PART NUMBER PVC Cotton Neoprene Silicone (Select by Type and Leadwire Insulation)	A½-001 — —	A1-001 A1-002 A1-003	G5Z-001 G5Z-002 G5Z-003	G8Z-001 G8Z-002 G8Z-003	G10Z-001 G10Z-002 G10Z-003
Max. Included Angle* *Switching occurs when body axis is near horizontal.	15°	15°	II°	9°	9°
ELECTRICAL RATINGS					
AC Amps, 60Hz 120V 240V 480V	1.0 0.4 —	1.0 0.7 —	7.0 5.0 —	15.0 11.0 8.0	25.0 19.0 13.0
DC Amps 120V 240V	0.5 0.4	0.5 0.4	5.0 4.0	8.0 6.0	13.0 10.0
Tungsten Lamp (120V, 60Hz), Watts	60	100	700	1000	1700
Motor Load, Horsepower AC 60Hz, 120-480V DC, 120-240V	Ξ	=	0.33 0.25	0.50 0.33	1.0 0.5
Contact Resistance Milliohms (Typical)	30	30	3	3	3
Standoff Voltage, Contact to contact Contact to ground	1250 1500	1500 5000	1500 5000	1500 5000	3000 5000
LEADWIRE INFORMATION Length, in. Terminal Hole Diameter Machine Screw Size	6 Spade 0.142 #6	6 Ring 0.170 #8	6 Ring 0.170 #8	6 Ring 0.203 #10	6 Ring 0.203 #10
ENGLISH DIMENSIONS Lbs./100 pcs. Body Length, in. (less leads) Max. Diameter, in.	0.99 0.96 0.38	3.04 1.31 0.50	4.45 1.81 0.52	8.64 2.03 0.75	13.05 2.38 0.84
METRIC DIMENSIONS Kg/100 pcs. Length, cm Max. Diameter, cm	0.45 2.44 0.95	1.38 3.33 1.27	2.02 4.60 1.37	3.92 5.15 1.91	5.92 6.03 2.14
MOUNTING CLIP Single Double	Ξ	122 2023	122 2023	122 2008	122 2009



Tel: (574)-264-6099 Ext 501

Tel: (888) 847-6552: Fax: (574) 293-8013

DURAKOOL Tip-Over and Motion Switches

Durakool Tip-Over switches are specified by the angle of travel away from the vertical required to "make" or "break" the contact. The operating angle designed for the installation must be larger than this specification to ensure proper switch action.

	designed for the i	nstallation must be larger th	an this specification to ensu	re proper switch action.		
TYPE/SERIES	тоз	TO8	TO8	TO8	A½S	A½S
PART NUMBER	TO3-1016 See Note 1	TO8-2009	20176	4539	4770	20243
Max. make/break angle (from 0° vertical reference)	10°/45°	12°/30°	10°/35°	25°/72°	15°/130°	Motion/vibration activated
Note: Switches are pictured in normally closed positions.						
ELECTRICAL RATINGS						
AC Amps, 60Hz 120V 240V DC Amps	12.5 6.0	1.7 0.75 1 (12VDC)	1.7 —	1.7 	0.5 (I2VDC)	0.5 (I2VDC)
Tungsten Lamp (120V, 60Hz), Watts	1500 (Resistive)		_	_	_	2_7
Motor Load, Horsepower AC 60Hz, I20-240V	0.167	-	r_=	_	8_0	2 <u>-</u> 2
Contact Resistance Milliohms (Typical)	Meets UL Heat Rise Specification	5 Ohms @ 5 Volts/10mA*	Varied by Application	0.02 Ohms @ 1 Volt/10mA*	20 Ohms @ ImA max.*	I Ohm @ 5 Volts/ ImA max.*
Standoff Voltage, Contact to Contact	1240	500	1240	500		200
ENGLISH DIMENSIONS Lbs./100 pcs. Body Length, in. (with leads) Max. Diameter, in.	3.20 0.87 0.94	1.7 .44 .477	0.77 1.08 0.60	0.77 0.65 0.60	0.84 0.27	0.31 0.627 0.31
METRIC DIMENSIONS Kg/100 pcs. Length, cm Max. Diameter, cm	1.45 2.21 2.40	0.76 1.13 1.22	0.35 2.74 1.52	0.35 1.65 1.52	2.12 0.67	0.13 1.6 0.79
Finish	Nickel	Acid Tin	Acid Tin	Nickel	Acid Tin	Acid Tin

Note 1:


TO3-1015 = $\frac{1}{4}$ " Male Quick Connect Center Elect. Mounting Terminal

TO3-1016 = 1/4" Male Quick Connect Center Elect., 1/4" Female 180°

TO3-1026 = $\frac{1}{4}$ " Male Quick Connect Center Elect., $\frac{1}{4}$ " Male 180°

*Varies by application

Tip-Over Switch





American Electronic Components, Inc 1101 Lafayette Street Elkhart, IN 46516 Tel: (574)-264-6099 Ext 501

Tel: (888) 847-6552: Fax: (574) 293-8013

DURAKOOL Specialty Switches

TYPE	Single-pole	Wide Angle
PART NUMBER	20110	5199
Max. Included angle (from 0° vertical reference)	30°	20°
DESCRIPTION		
	Must make between 45° and 75° from vertical.	Must make between 50° and 70° from vertical.
ELECTRICAL RATINGS		
AC Amps, 60Hz 12 VDC	10 mA (max) all voltages	10 mA (max) all voltages
ENGLISH DIMENSIONS Lbs./100 pcs. Body Length, in. (with leads) Max. Diameter, in.	0.33 0.74 0.31	0.32 0.52 0.31
AND RESIDENCE OF THE PERSON OF		

DURAKOOL Ball Switches

TYPE	Single-pole	Single-pole		
PART NUMBER	20518	20274		
Max. Included angle (from 0° horizontal reference)	± 5°	± 8°		
DESCRIPTION				
	Plated ball suitable for tip or tilt applications.	High current ball tilt switch, noise dampened.		
ELECTRICAL RATINGS	****			
AC Amps, 60Hz 13.5 VDC	5 mA (max)	I A (max)		
ENGLISH DIMENSIONS Lbs./100 pcs. Body Length, in. (with leads)	0.31 0.74	4.0 0.99		

American Electronic Components specializes in the design and manufacture of electronic, electrical, and mechanical components. AEC's products are shipped worldwide for a diverse set of markets which include automotive, consumer electronics, appliance, industrial control, and outdoor power equipment manufacturers. For more information, contact the AEC Sales Department



◄ Hermetic Seals

HERMASEAL Glass-to-Metal Hermetic Seals, Feedthrus & Deep Vacuum Brazing

Relays >

Hermetically sealed high power relays 10-150 amps for general and high voltage use.



⋖ Switches

Hermetically sealed tilt and tip-over switches for appliance, automotive, security, and safety use.



Electromechanical >

Starter solenoids for outdoor power equipment and solenoids for automotive seatbelt retractors.



Local Representative:



American Electronic Components, Inc. 1101 Lafayette Street Elkhart, IN 46516 Tel: (574) 264-6099 Ext 501 Tel: (888) 847-6552 Fax: (574) 293-8013